

KX-TA824 Quick Residential Setup _ via Keypad

Be sure to turn off power to PBX prior to any card installation / swapping or damage will occur!

To get into “System Program Mode”: Program, *#1234

System Programming >>> Key Mapping:

Next = SP-PHONE Store = AUTO DIAL

Select = AUTO ANSWER Back = REDIAL

⇒ = FWD/DND End = HOLD

⇐ = CONF All = *

Date / Time Set: [000]

Ringing Assignment: Day [408]

Ringing Assignment: Night [409]

Dial Out Assignment: Day [405]

Dial Out Assignment: Night [406]

CID Enable: [900] Enter program mode, dial 900, next, next, enable/disable by select button, store.

Toll Restriction:

- Start with [601] All Jacks - COS=2, end [602] All Jacks - COS=2.
COS-1 is default and will provide all access.
- Deny [302] Code 01= “0”, Code 02= “1”
- Allow [306] enter these Codes: 1800, 1855, 1866, 1877, 1888

Adding Station Names to Display: [604] Enter program mode, dial 604, next, next, and use dial pad keys to enter letters (the Select will scroll your options)

“Personal or Station Programming”

Auto CO Line Hunt: Push “Program”, then 1, 2 store. (from each station location)

Flexible Key Programming for CO Buttons: Push “Program”, then soft key (with LED light) to be programmed, dial 0 + CO number (ie. 0+1=CO 1)

Flexible Key Intercom Button Programming: Push “Program”, then soft key (with LED light) to be programmed, dial 1 + station location number (ie. 1+101= station 101)

CID Indicate Button: Push “Program”, then soft key with light, 96, store.

CID Select Button: Push another soft key with light, 97, store, end.

CID Answer Log: Press Intercom, then dial 7382# at EVERY extension.